(() qtx

BATPAR-18

Item ref: 154.045UK

Rechargeable Mini LED PAR Light

User Manual

Please read through this manual thoroughly before use, any damage caused by misuse of product will not be covered by warranty.



Small yet surprisingly powerful mini LED PAR light ideal for parties and events at home or in smaller venues. The integrated rechargeable battery which can be charged using the included USB lead, provides the convenience of up to 6 hours use without the need of a power supply. A simple switch on the back of the unit provides the choice of various automatic colour changing modes or a sound to light function. The included remote control offers an even wider variety of features making this little PAR light perfect for both home and professional use.

In the box:

Your BATPAR-18 should arrive with you in a single carton in good condition. The carton should contain $1 \times$ main unit with bracket and screws, $1 \times$ remote control, $1 \times$ UK IEC mains lead and $1 \times$ user guide.

Warning:

To prevent risk of fire or electric shock, do not expose the unit to rain or damp environments. In the event of a spillage, disconnect the charging lead and allow the unit to dry out naturally. Qualified personnel should then check the unit before continuing use.

Placement:

- Use the included mounting bracket to fix to a stand or lighting truss.
- The BATPAR-18 can also be surface mounted using the stand or even laid almost flat and used as an uplighter.
- Keep away from damp or dusty environments.

www.avsl.com

@qtx

Usage Instructions:

- Connect the USB charging lead provided to a suitable USB power supply and fully charge the unit before first use. You should receive up to 6 hours of normal use to a single charge.
- Use the switch on the back of the unit to choose between auto and sound to light modes, along with master power off.
- Please note: the supplied remote control will only work when the switch on the back of the unit is set to auto or sound to light modes.

Remote control:

The BATPAR-18 is supplied with an I.R. remote control for quick access the extended functions of the unit. This has a maximum range of approximately 4-5m and must be aimed towards the front of the unit. Controls and functions are listed on the diagram below:



- 1. ON/OFF = Remote on/off
- 2. Auto = Automatic mode
- 3. Jump = Colour jump mode
- 4. Fade = Colour fade mode
- 5. Red = Red colour open
- 6. Rose = Rose colour open
- 7. White = White colour open
- 8. -- = Decrease speed in auto modes
- 9. Strobe = Strobe on/speed adjust
- 10. Sound = Sound activated mode
- 11. Green = Green colour open
- 12. Blue = Blue colour open
- 13. Amber = Amber colour open
- 14. Cyan = Cyan colour open
- 15. + = Increase speed in auto modes

Specifications:

Power	5V 3.6A (lithium rechargeable)
Power consumption	18W
LED power	12x 1.5W RGB
Battery life	Up to 6 hours
Modes	Auto, sound activated
Dimensions	115 x 115 x 50mm
Weight	260g

This product is classed as Electrical or Electronic equipment and should not be disposed with other household or commercial waste at the end of its useful life. The goods must be disposed of according to your local council guidelines.

Errors and omissions excepted.

Copyright© 2022 AVSL Group Ltd, Unit 2 Bridgewater Park, Taylor Road, Trafford Park, Manchester. M41 7JQ. AVSL (Europe) Ltd, Unit 3D North Point House, North Point Bus. Park, New Mallow Road, Cork, Ireland.

www.avsl.com

154.045UK User Manual